

AUSTRALIA, AUSTRIA, BELGIUM, BULGARIA, CANADA, CHINA, CZECHIA, FRANCE, GERMANY, GREAT BRITAIN, HUNGARY, INDIA, INDONESIA, ITALY, MALAYSIA, MEXICO, NETHERLANDS, PERU, POLAND, REPUBLIC OF KOREA, SPAIN, SWITZERLAND, THAILAND, TUNISIA, TURKEY, USA, VIETNAM

KOBOLD Messring GmbH Nordring 22-24 D-65719 Hofheim/Ts. ► Head Office: +49(0)6192 299-0 € +49(0)6192 23398 info.de@kobold.com www.kobold.com



## Description

KOBOLD rotating vane flow meters series DRG are used for measuring and monitoring low viscous liquids.

Series DRG flow meters are working according the wellknown rotating vane principle. A magnet fitted in the vane and hermetically sealed from the medium transfers non-contacting the rotary motion to a Hall-effect sensor mounted in the housing. The sensor converts the rotary motion which is proportional to the flow to a frequency signal. A seriesconnected electronics unit converts the signal to an analogue output, limit contacts or display.

### **Fields of Application**

### Cooling water monitoring

- Agricultural machinery
- PCB board industry

# **Electrical Connection**

DRG-...F., DRG-...L3... 3-wire



DRG-...L342... 2-wire



DRG-...L4...



## **Technical Details**

Material combinations: Max. operating pressure: Max. temperature: Measuring accuracy:	see order details see order details see order details ±3% of full scale
Electrical connection:	plug connector DIN 43 650, plug connector M12x1
Pressure loss:	max. 1 bar at max. range
Protection:	IP 65
Electronics	
Frequency output (	F300)
Power supply:	12-28 V <sub>DC</sub>
Power consumption:	10 mA
Pulse output:	PNP, open collector max. 25 mA
Electrical connection:	plug connector M12x1
Frequency output with the second s	th frequency divider

Power supply:	24 V <sub>DC</sub> ±20%
Power consumption:	15 mA
Pulse output:	PNP, open collector, max. 25 mA
Electrical connection:	plug connector M12x1
Division ratio:	1 <sup>1</sup> / <sub>128</sub> , factory set

### Analogue output (Option plug-on display)

Power supply:	24 V <sub>DC</sub> ±20%
Output:	0-20 mA or 4-20 mA,
	2-wire or 3-wire
Max. load:	500 Ω
Electrical connection:	plug connector M12x1 or DIN 43650
Option:	plug-on display (with plug connector DIN 43650 and output 4-20 mA only), 2-wire

### Compact electronics

Display:	3-segment LED
Analogue output:	(0)420 mA adjustable, max. 500 W
Switching outputs:	1 (2) semiconductor PNP or NPN factory set
Contact operation:	N/C / N/O contact frequency programmable
Setting:	with 2 buttons
Power supply:	24 V <sub>DC</sub> ±20%, 3-wire technology approx. 100 mA
Electrical connection:	plug connector M12x1

No responsibility taken for errors; subject to change without prior notice.



Measur	ing range	Orifice diameter	Model	Connection		
Water [l/min]	approx. frequency [Hz] at F.S.	[mm]		Standard female	Special female	Evaluating electronics Frequency output
0.5-12	120	6	DRG-1×05	<b>G1.</b> .=G1/8	N1=1/8" NPT	<b>F300</b> = Frequency output, plug connector M12 x 1 <b>F320</b> = Frequency divider 1:2,
0.5-25	217	6	DRG-1X10	<b>G2</b> =G1⁄4	N2=1/4" NPT	plug connector M12 x 1 <b>F340</b> = Frequency divider 1:4, plug connector M12 x 1 <b>F390</b> = Frequency divider 1 <sup>1</sup> / <sub>128</sub> .
1 - 30	217	8	DRG-1X15	<b>G2</b> =G1⁄4	N2=1/4" NPT	plug connector M12x 1 Analogue output
1 - 30	190	7	DRG-1×15	<b>G4.</b> .=G½	N4=½"NPT	<b>L303</b> = 0-20 mA output, 3-wire, M12 x 1 plug connector <b>L342</b> = 4-20 mA output, 2-wire, M12 x 1 plug connector
2-45	215	8	DRG-1X20	<b>G4.</b> .=G½ <b>G5.</b> .=G¾ <b>G6.</b> .=G1	N4=½"NPT N5=¾ "NPT N6=1"NPT	<b>L343</b> = 4-20 mA output, 3-wire, M12 x 1 plug connector <b>L442</b> = 4-20 mA output, 2-wire, plug connector DIN 43 650
5-90	265	12	DRG-1X25	<b>G4</b> =G½ <b>G5</b> =G¾ <b>G6</b> =G1	N4=½"NPT N5=¾ "NPT N6=1"NPT	Compact electronics* C30R = LED display, 2 x open Collector, PNP, plug connector M12 x 1 C30M = LED display, 2 x open Collector, NPN, plug connector M12 x 1
5-140	116	16	DRG-1X30	<b>G5</b> =G¾	N5=¾ " NPT	C34P = LED display, 4-20 mA, 1 x open Collector PNP, plug connector M12 x 1 C34N = LED display, 4-20 mA, 1 x open Collector NPN, plug connector M12 x 1
10-140	180	16	DRG-1X35	<b>G6</b> =G1	N6=1"NPT	Conector MENA, plug connector MIT2 X T

# Order Details (Example: DRG-1105 G1 F300)

\* Please specify flow direction in writing.

### Material Combinations (Please enter order code instead of X "model")

Device parts	Order code: 1	Order code: 2	Order code: 4	Order code: 5	Order code: 8	Order code: 9
Housing	Brass	Brass	1.3955	1.3955	Polypropylene	Polypropylene
Housing cover	Polysulfone	Brass	Polysulfone	1.4404	Polypropylene	Polysulfone
Seal	NBR	NBR	FPM	FPM	NBR	NBR
Rotating vane	PTFE	PTFE	PTFE	PTFE	PTFE	PTFE
Axle	Ceramic	Ceramic	Ceramic	Ceramic	Ceramic	Ceramic
Bearing	PTFE	PTFE	PTFE	PTFE	PTFE	PTFE
p <sub>max</sub> :	16 bar	40 bar	16 bar	40 bar	7 bar	7 bar
t <sub>max</sub> :	80°C	80 °C	80 °C	80 °C	80°C	80 °C
Sensor Weight	580 g	580 g	480 g	480 g	120 g	120 g



### Plug-on Display

for model DRG...L442 (with 4-20 mA output and DIN plug connector)

Description	Order number
4-digit LED, connector DIN 43650, 2-wire, supply through analogue output	AUF-1000
as above however with additional open collector output	AUF-1001

### **Electronic weight**

Frequency output:approx. 35 gAnalogue output (...L3...):approx. 35 gAnalogue output (...L4...):approx. 100 gCompact electronics:approx. 650 g



# Dimensions

Model: DRG-F3... (with frequency output), DRG-..L3.. (with analogue output)



G*	А	В	С	Е	SW
1⁄8	80	16.5	63.0	72.5	24
1⁄4	80	16.5	63.0	72.5	24
1⁄2	80	16.5	63.0	72.5	24
3⁄4	100	25.0	69.5	90.0	38
1	100	25.0	69.5	90.0	38

Model: DRG-...L442 (with analogue output and plug-on display)



## Model: DRG-...C (with compact electronics)



G*	А	в	с	Е	SW
1⁄8	80	16.5	63.0	72.5	24
1⁄4	80	16.5	63.0	72.5	24
1⁄2	80	16.5	63.0	72.5	24
3⁄4	100	25.0	69.5	90.0	38
1	100	25.0	69.5	90.0	38

G*	А	В	С	E	SW
1⁄8	80	16.5	63.0	72.5	24
1⁄4	80	16.5	63.0	72.5	24
1⁄2	80	16.5	63.0	72.5	24
3⁄4	100	25.0	69.5	90.0	38
1	100	25.0	69.5	90.0	38

\* Screw-in depth acc. to DIN 3852-2 short version

No responsibility taken for errors;

subject to change without prior notice.